

Waveguide to Coaxial Adapter **AWR19185EL**



WR19 to 1.85mm Female, Round Cover Flange, End Launch

Rev 2

Electrical

Frequency Range	39.2-59.6 GHz
VSWR	1.4 max

Configuration

Waveguide Size	IEC	500
	EIA	WR19
Flange Type	IEC	/
	North America	UG383/U(Modified)
Coax Connector	1.85mm Female	
Body Geometry	End Launch	


Materials

Waveguide Body	Copper, gold plated
Connector Body	Passivated stainless steel
Center Contact	Gold plated beryllium copper

Mechanical & Environmental

Operating Temp	-40°C to +85°C
Connector Interface	IEC-61169
RoHS	Compliant

Typical Test Data



Waveguide to Coaxial Adapter **AWR19185EL**

WR19 to 1.85mm Female, Round Cover Flange, End Launch



Rev 2

Dimensions(mm)

