AWR19185M

WR19 to 1.85mm Male Waveguide to Coaxial Adapter
UG383/U Mod Flange, Right Angle



Rev 1

Electrical

Frequency Range	39.2-59.6 GHz
VSWR	1.35 max

Configuration

Waveguide Size	IEC	R500
	EIA	WR19
Flange	IEC	/
	North America	UG383/U(Modified)
Coax Connector	1.85mm Male	
Body Geometry	Right Angle	

Mechanical & Environmental

Waveguide Body	Cu, gold plated
Connector Body	Passivated stainless steel
Center Contact	Gold plated brass
Operating Temperature	-40℃ to +85℃
Connector Interface	IEC-61169
RoHS	Compliant under exemptions 6 (b) or 6 (c)
Net Weight	Approx 50g

AWR19185M





WR19 to 1.85mm Male Waveguide to Coaxial Adapter

UG383/U Mod Flange, Right Angle

Rev 1

Dimensions(mm)






AWR19185M

WR19 to 1.85mm Male Waveguide to Coaxial Adapter
UG383/U Mod Flange, Right Angle




Rev 1

Typical Test Data at 25℃



VSWR



Insertion Loss*

* In Insertion Loss (IL) testing, adapters are measured back-to-back. To obtain the loss of a single adapter, divide the measured value by two.