

Waveguide to Coaxial Adapter **AWR15185**

WR15 to 1.85mm Female, Round Cover Flange, Right Angle



Rev 4

Electrical

Frequency Range	50-70 GHz
VSWR	1.35 max

Configuration

Waveguide Size	IEC	620
	EIA	WR15
Flange Type	IEC	/
	North America	UG385/U
Coax Connector	1.85mm Female	
Body Geometry	Right Angle	


Materials

Waveguide Body	Copper, gold plated
Connector Body	Passivated stainless steel
Center Contact	Gold plated beryllium copper

Mechanical & Environmental

Operating Temp	-40°C to 70°C
Connector Interface	IEC-61169
RoHS	Compliant

Typical Test Data



Waveguide to Coaxial Adapter **AWR15185**

WR15 to 1.85mm Female, Round Cover Flange, Right Angle



Rev 4

Dimensions(mm)

