

1.0-1.8 GHz Band Pass Filter

BPF-1400MS1

RVA 1

Specifications

1	Center Frequency(F0)	1400MHz	
2	Pass Band Frequency	1000 ~ 1800MHz	
3	Pass Band Insertion Loss	≤1.5dB	
4	Pass Band Ripple	≤0.8dB	
5	Pass Band VSWR	≤1.5	
6	Stop Band Rejection	≥60dB @ DC~ 600MHz ≥30dB @ 600~ 800MHz	≥30dB @ 2200~2500MHz ≥60dB @ 2500 ~ 5000MHz
7	Impedance	50 Ohms	
8	Power Handling	2W max	
9	Connectors	SMA-Female	
10	Surface Finish	Black Painted	
11	Temperature Range	-30℃ ~ +70℃	

Dimensions(mm)

