

16.4-17.2 GHz Band Pass Filter

BPF-16800MS1

RVA 1

Specifications

1	Center Frequency(F0)	16800MHz	
2	Pass Band Frequency	16400 ~ 17200MHz	
3	Pass Band Insertion Loss	≤1.7dB	
4	Pass Band Ripple	≤0.7dB	
5	Pass Band VSWR	≤1.22	
6	Stop Band Rejection	≥80dB @ DC ~ 16000MHz ≥30dB @ 16000 ~ 16200MHz	≥30dB @ 17400 ~ 17600MHz ≥80dB @ 17600 ~ 32000MHz
7	Impedance	50 Ohms	
8	Power Handling	5W max	
9	Connectors	SMA-Female	
10	Surface Finish	Black Painted	
11	Temperature Range	-30℃ ~ +70℃	
12	Weight	About 95g	

Dimensions(mm)

