

# **Coaxial Fixed Attenuator**

# RFHB04XXBC2



### DC-4 GHz, 1-60 dB, 2 Watts, BNC, Bidirectional


Rev	3
-----	---

ectrical				
Impedance	50 ohm			
Frequency Range	DC-4 GHz			
VSWR	1.2 max			
Input Avg Power	2W@ 25 $^\circ C$ ambient, derating linearly to 0.2W at 100 $^\circ C$			
Peak Power	250W (5 micro-sec pulse width, 0.4% duty cycle)			
Direction	Bidirectional, BNC female to BNC male (other configurations available)			
Attenuation(dB)	1-6	7-20	21-30	40-60
Accuracy(dB)	±0.3	±0.5	±0.75	±0.8

#### Mechanical

Mechanical		Environmental	
Connector Body	Ternary alloy plated brass	Operating Temperature	<b>-55℃ to 100℃</b>
Heat Sink	N/A	Storage Temperature	<b>-55℃ to 125℃</b>
Center Contact	Gold plated beryllium copper/brass	RoHS	Compliant
Net Weight	About 18 g	Temperature Coefficient	<b>&lt;0.0004 dB/dB/</b> ℃

#### Dimensions(mm)



1-30dB: L=35 40-60dB: L=38

### Notes

1.Customized dB values, outlines and optimal accuracy/VSWR available.

#### **Model Description**

#### RFHB04XXBC2

1.XX for dB value: 06=6dB,30=30dB

2.Code for connector configuration:

A=female for two ends; B=male for two ends

C=female for one end and male for the other.