

Waveguide Termination

WT137A150

WR137, 5.38-8.17 GHz, 150 Watts, Rectangular Cover Flange

Rev 1

Electrical

Impedance	50 ohm
Frequency Range	5.38-8.17 GHz
VSWR	1.2 max
Input Avg Power	150 Watts @ 25°C
Peak Power	1.5 kWatts
Operating Temperature	-40°C~+70°C

Mechanical

Waveguide Size	WR137(R70)
Flange Type	IEC: UDR70
Waveguide Material	Aluminum
Waveguide Finish	Black painted
Heat Sink Material	Aluminum
Heat Sink Finish	Black painted

Dimensions(mm)

