

Waveguide Termination

WT137A2000

WR137, 5.38-8.17 GHz, 2000 Watts, Rectangular Cover Flange

Rev 1

Electrical

Frequency Range	5.38-8.17 GHz
VSWR	1.2 max
Input Avg Power	2000 Watts @ 25°C
Peak Power	20 kWatts
Operating Temperature	-40°C ~ +70°C

Mechanical

Waveguide Size	WR137(R70)
Flange Type	IEC: UDR70
Waveguide Material	Aluminum
Waveguide Finish	Black painted
Heat Sink Material	Aluminum
Heat Sink Finish	Black painted
Net Weight	Approx 9kg

Dimensions(mm)

