

Waveguide Termination

WT187A

WR187, 3.94-5.99 GHz, 8 Watts, Rectangular Cover Flange



Rev 1

Electrical

Frequency Range	3.94-5.99 GHz
VSWR	1.03 max
Input Avg Power	8 Watts @ 25°C
Operating Temperature	-40°C ~ +70°C

Mechanical

Waveguide Size	WR187(R48)
Flange Type	IEC: UDR48
Waveguide Material	Aluminum
Waveguide Finish	Grey painted

Dimensions(mm)

